

electribe sampler Ver 1.06 Release Information

Changes in Ver1.06 from Ver.1.05

- A few low-level software bugs have been fixed.

What you will need

- Memory card supported by electribe sampler
- Computer with memory card adapter
- AC adapter KA350 or six AA batteries



Make sure the batteries are brand new if using alkaline or fully charged if using NiMH batteries.

Updating the software

- Prepare a memory card that has been formatted by electribe sampler.
- Insert the memory card into your card reader, and connect it to your computer.
- Extract electribe_sampler_xxxx.zip
- Copy “SYSTEM.VSB” into the [SYSTEM] folder under the [KORG][electribe sampler] folder on the memory card.
- Insert the memory card containing the new system file into your electribe sampler, and turn on the power.
- Select “SOFTWARE UPDATE” from the DATA UTILITY menu. Press Menu/Enter.

```
Data Util 26/27  EDIT  █  █
DATA UTILITY
press [ Enter ]
```

```
Data Util 13/13  EDIT  █
SOFTWARE UPDATE
press [ Enter ]
```

- Current version and new version will appear. Press Menu/Enter button.

```

Data Util 13/13  E01Y  1 00
SOFTWARE UPDATE
Now Version : 1.05
Next Version : 1.06
press [ Enter ]

```

- A confirmation message will appear. Press Menu/Enter button to begin the update operation.

```

Data Util 13/13  E01Y  1 00
SOFTWARE UPDATE
Are You Sure ?
press [ Enter ]

```



Do not turn off electribe sampler while update is in progress.

- electribe sampler will display the following screen when update is complete.

```

Data Util 13/13  E01Y  1 00
SOFTWARE UPDATE
OK. Please Reboot.

```

- Long push the power button. electribe sampler will now turn off. The system has been updated.